

***BlueEyes***<sup>®</sup>

# DDS Server

## Operation manual

Ver. 4

2016/10/06

[www.BlueEyestech.com](http://www.BlueEyestech.com)



# Operation manual

## □ DDS Server

Thank you for using the product of BlueEyes Technology.

The manual will introduce the product of BlueEyes Technology. Please read the manual before you start using the product.

Though the information in the manual has been verified before publish, the actual specification should be based on the actual shipment. BlueEyes Technology doesn't have to guarantee, proclaim or declare for the content, along with other purpose. In addition, the product specification and information that mentioned in the manual is for reference only. The content might be update at any time without notice. If there is any mistake of the information, including software, firmware, and hardware that mentioned in the manual BlueEyes Technology has no responsibility for the mistake.

Please reach BlueEyes website to get the upgrade of the product specification, our company will not notice you. If you want to get the latest product information, operation manual, firmware, or you have any question to the products of BlueEyes Technology, please contact your local agent or go to the official website of BlueEyes Technology for further information.

It is not allowed to copy/ use the content or to change the information and publishing of the manual without BlueEyes Technology's written consent.

Copyright 2016 BlueEyes Technology Inc. All Rights Reserved.

## BlueEyes Technology Corp.

Add: 7F-3, No.200, Sec. 4, Wenxin Rd., North District, Taichung City 40462, Taiwan

TEL: +886 4 2297 0977 / +886 982 842 977

Fax: +886 4 2297 0957

E-mail : support@blueeyes.com.tw

Website: www.BlueEyestech.com



# Index

1. Introduction .....	3
1.1 About the manual.....	3
1.2 Intellectual Property Rights .....	3
1.3 About the manual.....	3
2. Install VM.....	4
2.1 VMware player.....	4
2.2 Setup VMware player .....	9
2.3 Database Management Interface .....	17
3. Admin.....	18
3.1 Information .....	18
3.2 Account Management .....	19
4. Company .....	20
4.1 Information .....	20
4.2 Scrolling Text Management.....	21
4.3 Instant message Management .....	22
4.4 Content Management.....	23
4.5 DDS PRO Management.....	26
4.6 URL Management.....	26
4.7 Location Management .....	29
4.8 Player Management .....	31
4.9 Player Status .....	34
4.10 Server Settings.....	35
5. Q&A.....	36
Q1: What is default account and password for admin? .....	36
Q2 How to I know connection for DDS PRO ? .....	36
Q3: Can I send Instant message to specific DDS PRO ? .....	36
Q4: Show insufficient capacity while updating ? .....	36

# 1. Introduction

## 1.1 About the manual

The manual can help you understand the function and operation methods of DDS player

- The company suggested you that if you store all written records of important information, in some cases, it may cause data loss and change in the electrical storage. Therefore the company is not responsible for the data loss that is caused by improper use, maintenance, defects, expire or any other reason.
- The company is not responsible for the economy loss that is caused by the third party or other function, such as the DIY firmware, the information loss or change.
- The pictures of operation manual may be different from the actual product, this is because of the software version changes.
- If there are changes of the information in the manual, we would not notice you. Please go to the official website of BlueEyes Technology.
- The company would not be responsible for the information downloaded from the website.

## 1.2 Intellectual Property Rights

According to the Intellectual Property Rights, the copy, changes, or usage of copyrighted pictures and music are only for personal or private use. If the user does not have a wider range of copyright or not explicit consent of the copyright owner and unauthorized copying, change or use the copies of this way to change or make or amendment, then it would be viewed as violating copyright laws. The copyright owner is entitled to claim for loss. For this reason, do not illegally use copyrighted materials.

## 1.3 About the manual


- Please read the instructions carefully before use, our company is not responsible for the artificial problems caused by incorrect use of the product.
- Read and keep instructions properly. Operate according to instructions in the operation manual.
- The pictures on the manual may be different from the pictures on the monitor. This is because the software version is different.

## 2. Install VM

### 2.1 VMware player


#### Step One、Download VMware player

Download address:[http://dds.blueeyes.com.tw/DDServer\\_download.php](http://dds.blueeyes.com.tw/DDServer_download.php)




#### Step Two、Unzip file

Unzip VMware-player-6.0.6-2700073.zip




#### Step Three、Process

Click VMware-player-6.0.6-2700073.exe




## Step Four、VMware player


Click “next” button




Choose “I accept the terms in the license agreement” and click “next” button.




Click “next” button.




Click “Continue” button.



Please wait while and Program installation



Click "Finish" button then Setup complete



After install VMware Player successfully, the VMware Player application icon as below display on desktop.




## 2.2 Setup VMware player


Click Open a Virtual Machine.




Browser and select DDSserver.vmx




Play virtual machine.



Click in the virtual screen to send keystrokes. Fill in the default account and password (user name: root and password: 27507522)



Fill in “ifconfig” command to get the ip address



```
DDSserver - VMware Player (Non-commercial use only)
Player
Ubuntu 14.04.4 LTS ubuntu tty1
ubuntu login: root
Password:
Last login: Thu May 5 15:08:09 CST 2016 on tty1
Welcome to Ubuntu 14.04.4 LTS (GNU/Linux 4.2.0-27-generic i686)

* Documentation:  https://help.ubuntu.com/


System information as of Mon May 9 17:48:06 CST 2016

System load: 0.56           Memory usage: 3%   Processes:      86
Usage of /:  1.5% of 97.07GB Swap usage:   0%   Users logged in: 0

Graph this data and manage this system at:
https://landscape.canonical.com/

root@ubuntu:~#
```

Your IP address are as below red rectangle.



```
DDSserver - VMware Player (Non-commercial use only)
Player
Welcome to Ubuntu 14.04.4 LTS (GNU/Linux 4.2.0-27-generic i686)

* Documentation:  https://help.ubuntu.com/

System information as of Wed May 11 09:59:49 CST 2016

System load: 0.64           Processes:      88
Usage of /:  1.5% of 97.07GB Users logged in: 0
Memory usage: 5%           IP address for eth0: 192.168.1.225
Swap usage:  0%

=> There are 2 zombie processes.


Graph this data and manage this system at:
https://landscape.canonical.com/

root@ubuntu:~# ifconfig
eth0      Link encap:Ethernet  HWaddr 00:0c:29:61:c4:89
          inet addr:192.168.1.225 Bcast:192.168.1.255 Mask:255.255.255.0
          inet6 addr: fe80::20c:29ff:fe61:c489/64 Scope:Link
          UP BROADCAST RUNNING MULTICAST  MTU:1500 Metric:1
          RX packets:1731 errors:0 dropped:103 overruns:0 frame:0
          TX packets:51 errors:0 dropped:0 overruns:0 carrier:0
          collisions:0 txqueuelen:1000
          RX bytes:112930 (112.9 KB) TX bytes:6784 (6.7 KB)
          Interrupt:19 Base address:0x2000

lo        Link encap:Local Loopback
          inet addr:127.0.0.1 Mask:255.0.0.0
          inet6 addr: ::1/128 Scope:Host
          UP LOOPBACK RUNNING  MTU:65536 Metric:1
          RX packets:36 errors:0 dropped:0 overruns:0 frame:0
          TX packets:36 errors:0 dropped:0 overruns:0 carrier:0
          collisions:0 txqueuelen:0
          RX bytes:2608 (2.6 KB) TX bytes:2608 (2.6 KB)

root@ubuntu:~#
```

Fill in “vi /etc/network/interfaces” and press Enter.



```
DDServer - VMware Player (Non-commercial use only)
Player
Password:
Last login: Wed May 11 10:00:49 CST 2016 on tty1
Welcome to Ubuntu 14.04.4 LTS (GNU/Linux 4.2.0-27-generic i686)

* Documentation:  https://help.ubuntu.com/

System information as of Wed May 11 10:08:59 CST 2016

System load:  1.04          Processes:      81
Usage of /:   1.5% of 97.07GB Users logged in:  0
Memory usage: 4%          IP address for eth0: 192.168.1.225
Swap usage:   0%

Graph this data and manage this system at:
https://landscape.canonical.com/

root@ubuntu:~# ifconfig
eth0      Link encap:Ethernet  HWaddr 00:0c:29:61:c4:89
          inet addr:192.168.1.225  Bcast:192.168.1.255  Mask:255.255.255.0
          inet6 addr: fe80::20c:29ff:fe61:c489/64 Scope:Link
          UP BROADCAST RUNNING MULTICAST  MTU:1500  Metric:1
          RX packets:233 errors:0 dropped:13 overruns:0 frame:0
          TX packets:49 errors:0 dropped:0 overruns:0 carrier:0
          collisions:0 txqueuelen:1000
          RX bytes:14571 (14.5 KB)  TX bytes:6263 (6.2 KB)
          Interrupt:19 Base address:0x2000

lo        Link encap:Local Loopback
          inet addr:127.0.0.1  Mask:255.0.0.0
          inet6 addr: ::1/128 Scope:Host
          UP LOOPBACK RUNNING  MTU:65536  Metric:1
          RX packets:36 errors:0 dropped:0 overruns:0 frame:0
          TX packets:36 errors:0 dropped:0 overruns:0 carrier:0
          collisions:0 txqueuelen:0
          RX bytes:2608 (2.6 KB)  TX bytes:2608 (2.6 KB)

root@ubuntu:~# vi /etc/network/interfaces
```



Fill in below command and press [Esc] to leave the edit page.


```
auto eth0
```

```
iface eth0 inet static
```

```
address 192.168.1.225
```

```
netmask 255.255.255.0
```

```
gateway 192.168.1.1
```



DDSserver - VMware Player (Non-commercial use only)

```
# This file describes the network interfaces available on your system
# and how to activate them. For more information, see interfaces(5).


# The loopback network interface
auto lo
iface lo inet loopback

# The primary network interface
auto eth0
iface eth0 inet static
address 192.168.1.225
netmask 255.255.255.0
gateway 192.168.1.1
```





Press [ I ] can insert the text. Edit address as below red rectangle . Press [ shift ]+[ : ] and fill in “wq” command and press [Enter]



```
DDServer - VMware Player (Non-commercial use only)
Player
<?php
$server_hostname="http://192.168.1.225/blueeyes/";
return $server_hostname;
?>
```

When you finish setting, you can use the website.

Ex : Ubuntu server IP : <http://192.168.1.225/blueeyes/>

## 2.3 Database Management Interface

Use browser to link : <http://192.168.1.225/phpmyadmin>

Fill in phpmyadmin root login company username and password  
(user name: root and password:27507522)




The screenshot shows the phpMyAdmin login interface. At the top, there is a logo for phpMyAdmin and the text "Welcome to phpMyAdmin". Below this, there is a "Language" section with a dropdown menu set to "English". Underneath is a "Log in" section with a "Log in" button. The "Log in" section contains two input fields: "Username:" with the value "root" and "Password:" which is empty. At the bottom right of the "Log in" section is a "Go" button.

### 3. Admin

Key in the user name and password, please click Login button to login the Digital Signage Management Server:

Admin User name:root

Admin password: 27507522



**Login to DDS Server Control Panel**

Company Username

Password


Choose Language: English ▾

Keep login in 30days

Login

#### 3.1 Information

PC information panel shows current status includes CPU Usage Rate、 RAM Usage Rate (Free/Total MB)、 HD Usage Rate (has already used %)、 System on time(More than days)



**DDS Server** | BLUEEYES TECHNOLOGY

Now Loaded Company: Admin

Information  
Account Management  
Server Settings

**Information**

PC Information

CPU Usage Rate	RAM Usage Rate(Free/Total MB)	HD Usage Rate(has already used %)	System on time(More than days)
0.14	731 / 1000	1%	4

## 3.2 Account Management

Click Account Management button the left side to create new account, you can create accounts for different companies, groups.


For example:

- Name : blueeyes\_Test
- Company Username : blueeyes
- Password : blueeyes
- Permission : Company or Admin



The screenshot shows the 'Account Management' section with a sidebar on the left containing 'Information', 'Account Management', and 'Server Settings'. The main area is titled 'New Account' and contains four input fields: 'Name', 'Company Username', 'Password', and 'Permission'. The 'Permission' dropdown menu is currently set to 'Company'. An orange 'Submit' button is located at the bottom left of the form.

After submit, you'll see the created account item in below, please click the Edit or Delete button.



The screenshot shows the 'Edit Account' section with a table listing accounts. The table has columns for 'Num.', 'Name', 'Company Username', 'Permission', and 'Action'. There are two rows of data. The first row has '1' in the 'Num.' column, 'blueeyes\_test' in 'Name', 'blueeyes' in 'Company Username', and 'Company' in 'Permission'. The 'Action' column for this row contains 'Edit' and 'Delete' buttons. The second row has '2' in the 'Num.' column, 'root' in 'Name', 'root' in 'Company Username', and 'Admin' in 'Permission'. The 'Action' column for this row contains 'Edit' and 'Delete' buttons. Above the table, there is a 'Show 10 entries' dropdown and a search box.

Num.	Name	Company Username	Permission	Action
1	blueeyes_test	blueeyes	Company	<a href="#">Edit</a> <a href="#">Delete</a>
2	root	root	Admin	<a href="#">Edit</a> <a href="#">Delete</a>

## 4. Company

Key in the user name and password you created

**Login to DDS Server Control Panel**

Company Username

Password

Choose Language: English ▾

Keep login in 30days

Login

### 4.1 Information

PC information panel shows current status includes CPU Usage Rate, RAM Usage Rate (Free/Total MB), HD Usage Rate (has already used %), System on time(More than days).

**DDS Server** | BLUEEYES TECHNOLOGY

Now Loaded Company: blueeyes

**Information**

Scrolling Text Management

Instant message Management

Content Management

DDS PRO Management

URL Management

Location Management

Player Management

Player Status

Server Settings

**Information**

PC Information

CPU Usage Rate	RAM Usage Rate(Free/Total MB)	HD Usage Rate(has already used %)	System on time(More than days)
0.13	898 / 1000	1%	5

DDS Player Information

blueeyes Player Total

0

## 4.2 Scrolling Text Management

Click Scrolling Text Management button in the left side. Scrolling Text Management allows you to manage the scrolling text name, scrolling text content(or upload text file as utf-8 format), Scrolling speed ,Polling time(1~100 min) , text style, text color, text size, text position, text play type.

<b>Information</b>	<h3>Scrolling Text Management</h3> <h4>Add Scrolling</h4> <p>Scrolling name <input type="text"/> (Letters, numbers, and underscores only please)</p> <p>Scrolling text <input type="button" value="選擇檔案"/> 未選擇任何檔案 <input type="button" value="Upload"/></p> <p>Note 1: Please save text file as utf-8 format if display garbled text. Note 2: Text file only accepted first line.</p> <div style="border: 1px solid #ccc; height: 40px; width: 100%;"></div> <p>50 characters remaining</p> <p>Scrolling speed <input type="text" value="Fast"/></p> <p>Polling time <input type="text" value="5"/> (1~100 min.)</p> <p>Text style <input type="text" value="Normal"/></p> <p>Text color <input type="text" value="White"/></p> <p>Text size <input type="text" value="Small"/></p> <p>Text position <input type="text" value="Top"/></p> <p>Text start from <input type="text" value="Left-to-Right"/></p> <p>Note <span style="color: red;">This Scrolling will be invalid when using DDS file.</span></p> <input type="button" value="Submit"/>
<b>Scrolling Text Management</b>	
<b>Instant message Management</b>	
<b>Content Management</b>	
<b>DDS PRO Management</b>	
<b>URL Management</b>	
<b>Location Management</b>	
<b>Player Management</b>	
<b>Player Status</b>	
<b>Server Settings</b>	

After submit, you'll see the created Scrolling item in below. If you want to change the content or delete it, please click the Edit or Delete button.

Note 1: Please save text file as utf-8 format if display garbled text.  
 Note 2: Text file only accepted first line.

50 characters remaining

Scrolling speed:

Polling time:  (1~100 min.)

Text style:

Text color:

Text size:

Text position:

Text start from:

Note: This Scrolling will be invalid when using DDS file.

---

Edit Scrolling

Scrolling name	Action
BlueEyes	<input type="button" value="Edit"/> <input type="button" value="Delete"/>

### 4.3 Instant message Management

- Click Instant message Management button in the left side.
- Instant message Management allows you to manage the scrolling text name, scrolling text content(or upload text file as utf-8 format),Transparent ,Display second(1~100 sec) , text color, text size. For example:

Information

Scrolling Text Management

Instant message Management

Content Management

DDS PRO Management

URL Management

Location Management

Player Management

Player Status

Server Settings

#### Instant message Management

Add message

Message name:  (Letters, numbers, and underscores only please)

Message text:  未選擇任何檔案

Note 1: Please save text file as utf-8 format if display garbled text.  
 Note 2: Text file only accepted first line.

20 characters remaining

Transparent:

Display second:  (1~100 sec.)

Text color:

Text size:

After submit, you'll see the created Instant message item in below.  
If you want to change the content or delete it, please click the Edit or Delete button.

The screenshot displays a web interface for configuring and managing instant messages. It is divided into three main sections:

- Send message now:** This section allows for configuring a new message. It includes dropdown menus for 'Transparent' (set to 'True'), 'Text color' (set to 'White'), and 'Text size' (set to 'Small'). There is a text input for 'Display second' (set to '5') with a note '(1~100 sec.)'. A 'Submit' button is located below these options.
- Edit message:** This section allows for editing an existing message. It includes a dropdown menu for 'Message name' (set to 'None') and a label for 'Time of last send'. A 'Submit' button is located below these options.
- Message List:** A table showing existing messages. The table has two columns: 'Message name' and 'Action'. One message is listed with the name 'BlueEyes'. The 'Action' column contains two buttons: 'Edit' (blue) and 'Delete' (red).

If you want to play Instant message, please select message name then click submit button, Time of last send will display time of send.


This screenshot shows the 'Send message now' configuration section. It includes a dropdown menu for 'Message name' (set to 'None') and a label for 'Time of last send'. A 'Submit' button is located below these options.

## 4.4 Content Management


Content Management allows you to add the photo or video content.

### Step One、Upload

Browser and select the file you want to upload. Please note that the content file is limited to 4GB and can only upload photo in jpg, jpeg, png file and Video in mp4, mpeg, avi file.



After submit, you'll see the created content in below. If you want to remove content, please click the Delete button.



## Step Two、 Play List Management

Select the contact file, if you want to play multi files, please click the “Add Content” button on the top to select new content file. You can click Remove button to delete the extra content.

The photo can set play time Sec(1~99). The video playback depend on Video length.

- Play List name: key in the playlist name(Letters, numbers, and underscores only please), for example: play151104
- Play List type: support Normal type (Limited 4GB) and Break type (Limited in 100MB).
- Orientation : Support Landscape and Portrait.

**Add Content**

Content Playlist

Add Content

 waste\_green\_landscape.jpg:1MB Sec: 5

Playlist name  (Letters, numbers, and underscores only please)

Playlist type Normal (Total content limited 2GB) ▾

Orientation Landscape ▾

**Submit**

## Step Three, Done

After submit, you'll see the created Play List item in below. If you want to change the Play List item or delete it, please click the Edit or Delete button.

\*Please note that you can only edit the content file, but can't change the Play List name and Play List type.

Content Playlist

Add Content

 waste\_green\_landscape.jpg:1MB Sec: 5

Playlist name  (Letters, numbers, and underscores only please)

Playlist type Normal (Total content limited 2GB) ▾

Orientation Landscape ▾

**Submit**

---

**Edit PlayList**

Show 10 ▾ entries Search:


Playlist name	Size	Playlist type	Orientation	Action
BlueEyes	1MB	Normal	Landscape	<b>Edit</b> <b>Delete</b>

## 4.5 DDS PRO Management


Click DDS PRO Management button in the left side.

DDS PRO Management allows you to add the DDS file, add DDS content:

- Upload file: select the DDS file you want to upload.
- Play List type: support Normal type(limited to 4GB) and Break type (limited to 100MB).



After submit, you'll see the created the DDS list in below. If you want to delete DDS file, please click the Delete button.



## 4.6 URL Management

Click URL Management button in the left side. URL Management allows you to add the URL website.

### Step One、Add URL

- URL Name : key in the URL name (Letters, numbers, and underscores only please)  
for example: BlueEyes
- URL Path : key in the URL Path, for example: http://blueeyes.com.tw/

After submit, you'll see the created the URL list in below. If you want to change the URL item or delete it, please click the Edit or Delete button.

URL Name	URL Path	Action
blueeyes	http://blueeyes.com.tw/	<a href="#">Edit</a> <a href="#">Delete</a>

## Step Two、 Add Play List

Click Play List button in the up side. Play List allow you to manage the play URL content and order that you would like to play on DDS PRO.

Select the URL name, if you want to play multi URL, please click the “Add Content” button on the top to select new URL name and Sec(10~65535). You can click Remove button to delete the extra URL.

- Play List name: key in the playlist name, for example: play151104, (Letters, numbers, and underscores only please)
- Play List type: support Normal type and Break type.
- Orientation : support Landscape and Portrait.

The screenshot shows the 'Add URL' form with the 'Playlist' tab selected. It includes an 'Add Content' button, a dropdown menu for 'blueeyes', a 'Sec' input field with the value '10' and a range '(10~65535)', a 'PlayList name' input field with a note '(Letters, numbers, and underscores only please)', a 'PlayList type' dropdown menu set to 'Normal', and an 'Orientation' dropdown menu set to 'Landscape'. A 'Submit' button is located at the bottom left.

## Step Three、 Done

After submit, you’ll see the created Play List item in below. If you want to change the Play List item or delete it, please click the Edit or Delete button. Please note that you can only edit the content file, but can’t change the Play List name ,Play List type and Orientation.

The screenshot shows the 'Edit PlayList' interface. At the top, there is a 'Show 10 entries' dropdown and a search box. Below is a table with the following columns: 'PlayList name', 'PlayList type', 'Orientation', and 'Action'. The table contains one row with the following data: 'BlueEyes', 'Normal', 'Landscape'. The 'Action' column for this row contains 'Edit' and 'Delete' buttons.

PlayList name	PlayList type	Orientation	Action
BlueEyes	Normal	Landscape	<a href="#">Edit</a> <a href="#">Delete</a>

## 4.7 Location Management

Click Location Management button in the left side. Location Management enables user to create a location and corresponding playlist content and play schedule.

- Location name: key in the location name.
- Marquee: select the Scrolling Text.(Support play content and URL)
- Check type: End play(DDS content default 10 min) 、 xx minutes(1~100) or xx o'clock.
- Schedule: enable you to set up the play time and play content (you can choose one of content 、 DDS 、 URL).

**Location Management**

**Add Location**

Location Name  (Letters, numbers, and underscores only please)

**Default Player Setting**

Scrolling text  This Scrolling will be invalid when using DDS file.

Check type  Content and URL file:End play, DDS PRO file:default 10 min    Start time o'clock

Auto delete expired schedule  No  Yes

Schedule

None  Add

For example

2016/05/30 16:00~2016/05/30 17:00 play [Playlist]BlueEyes.zip

2016/05/30 17:00~2016/05/30 18:00 hibernation

2016/05/30 18:00~2016/05/30 19:00 play[HTML5] BlueEyes.zip

**Location Management**

**Add Location**

Location Name  (Letters, numbers, and underscores only please)

**Default Player Setting**

Scrolling text:  This Scrolling will be invalid when using DDS file.

Check type:  Content and URL file:End play, DDS PRO file:default 10 min  (1~100 min.)  Start time o'clock

Auto delete expired schedule:  No  Yes

Schedule:

<input type="radio"/> None	<input checked="" type="radio"/> Add	<input type="text" value="2016/05/30"/>	<input type="text" value="16"/>	<input type="text" value="2016/05/30"/>	<input type="text" value="17"/>	<input type="text" value="[Playlist]BlueEyes.zip"/>
		<input type="text" value="2016/05/30"/>	<input type="text" value="18"/>	<input type="text" value="2016/05/30"/>	<input type="text" value="19"/>	<input type="text" value="[HTML5]BlueEyes.zip"/>

- Commercial Break Content for Routines Schedule

For example

Start date : 2016/05/30

End date : 2016/05/30

Start time : 17 : 30

End time : 18 : 00

The content will play [Playlist]NEWS.zip at 17 : 30~18 : 00 on 2016/05/10

**Commercial Break Content for Routine Schedule**

None  Add

:   :

After submit, you'll see the created location item in below. If you want to change the location item or delete it, please click the Edit or Delete button.

**Edit Location**

Show  entries Search:

Location Name	Action
taichung	<input type="button" value="Edit"/> <input type="button" value="Delete"/>

## 4.8 Player Management

Click Player Management button in the left side. Player management enable user to manage the players in different location and player device.

The screenshot shows a web application interface for Player Management. On the left is a sidebar menu with the following items: Information, Scrolling Text Management, Instant message Management, Content Management, DDS PRO Management, URL Management, Location Management, Player Management (highlighted), Player Status, and Server Settings. The main content area is titled 'Player Management' and contains a sub-section 'Add Player'. This section has two tabs: 'Excel File Input' (selected) and 'Single Input'. Below the tabs, there is a red note: 'Please use the CSV editor. Auto fill default value if field is null in sample file.' There is an 'Import File' field with a file selection button labeled '選擇檔案' and the text '未選擇任何檔案'. Below this is a 'Download Example Format File' section with a blue 'Download' button. At the bottom of the 'Add Player' section is an orange 'Submit' button.

Excel File Input:

Excel file input: User can download csv sample file to edit and upload batch data to manage the players at one time.

This screenshot is identical to the one above, showing the 'Player Management' interface with the 'Add Player' section. The 'Excel File Input' tab is selected, and the interface includes the same note, file selection field, download button, and submit button.

Click the Download button and save the csv file in PC, the file name is player\_example. We edit the csv file as below for example.

	A	B	C
1	Location name	Dev name	
2	taipei	taipei01	
3	taipei	taipei02	
4	taipei	taipei03	
5	hsinchu	hsinchu02	
6	hsinchu	hsinchu03	
7	hsinchu	hsinchu04	
8			

Browser the edited csv file and submit, you'll see the created player items in below.  
 If you want to change the player item or delete it, please click the Edit or Delete button.

Dev Name	Location	Status	Action
hsinchu02	hsinchu	Inactive	<a href="#">Edit</a> <a href="#">Delete</a>
hsinchu03	hsinchu	Inactive	<a href="#">Edit</a> <a href="#">Delete</a>
hsinchu04	hsinchu	Inactive	<a href="#">Edit</a> <a href="#">Delete</a>
taipei01	taipei	Inactive	<a href="#">Edit</a> <a href="#">Delete</a>
taipei02	taipei	Inactive	<a href="#">Edit</a> <a href="#">Delete</a>
taipei03	taipei	Inactive	<a href="#">Edit</a> <a href="#">Delete</a>

### Single Input:

- Location Name: select the location you created, for example: taichung
- Device Name: key in devices name, for example: taichung 1
- Setting Mode: support Location mode or Manual mode. Location mode: After selecting the location Name, the value will show automatically according to the location management you set up before. If you want to change, just select manual item to edit.

**Add Player**

Excel File Input | **Single Input**

Location Name: taichung

Dev Name:  (Letters, numbers, and underscores only please)

Setting Mode:  Location  Manual

Scrolling text: None This Scrolling will be invalid when using DDS file.

Check type:  Content and URL file:End play, DDS PRO file:default 10 min  0 (1~100 min.)  Start time o'clock

Auto delete expired schedule:  No  Yes

Schedule: 2016/05/30 16 2016/05/30 17 [Playlist]BlueEyes.zip


When the device connect ,the status will show “MAC(ex : 000ffdab2701)”.  
 If you want to change the player item or make it disconnect, please click the Edit or Cancel active button .The active device can't be deleted.  
 When the device disconnect, the status will show “Inactive”.

If you want to change the player item or delete it, please click the Edit or Delete button .



## 4.9 Player Status

You can see all players' working status in the status page. The server will check the status of each player device per interval time. For example : If the status is green(log is 200), it means the player is playing the media content.



Click the Show log Code button, you'll see the meaning of any status as below.

Log Code		
	101	Unzip fail
	102	Inactive
	104	Download fail
%	105	Downloading
	106	Unzipping
	107	Background Downloading
	108	Entry Setting Page
	200	Success

## 4.10 Server Settings

Click Server settings button in the left side.

Server settings enable user to manage the players limit the number of player to download.

Download unlimited number of devices in the same time when limit the number of player to download as Off.

Download limited number of devices(1~999) in the same time when limit the number of player to download as On.

Information	<div style="background-color: #e0f0ff; padding: 5px;"><b>Server Settings</b></div> <p>Limit the number of player to download <input checked="" type="radio"/> Off <input type="radio"/> On <input type="text" value="0"/> players</p> <p><input type="button" value="Save"/></p>
-------------	--

## 5. Q&A

**Q1: What is default account and password for admin?**

**【Answer】** Default account is root. Default password is 27507522.

**Q2 How to I know connection for DDS PRO ?**

**【Answer】** Go to Player status to check DDS PRO connection.

**Q3: Can I send Instant message to specific DDS PRO ?**

**【Answer】** No.

Instant message will send to all DDS PRO.

**Q4: Show insufficient capacity while updating ?**

**【Answer】** Unzip archive need twice the capacity. If your archive is 2GB, DDS PRO require 4GB storage space when updating via internet. Therefore, you need to ensure the capacity of archive which DDS PRO is playing plus twice the capacity of archive which you are going to updating is less than 5GB.





**BlueEyes<sup>®</sup>**  
*<http://www.BlueEyes.com.tw>*